



### DIESEL GENERATING SET 440/254V - 60 Hz - 3PHASE

POWER RATING		PRIME	STANDBY
POWER	kVA	130	143
	kW	104	114
Rated Speed	r.p.m	1800	
Available Voltages	V	480/277-440/254-220/127-208/120 etc	
Rated at power factor	Cos Phi	0.8	

**Standard Reference Conditions:** 25°C (77°F) Air Inlet Temp, 100m(328 ft) A.S.L. 30% relative humidity.

**Prime Power (PRP):**

According to ISO 8528-1:2018, Prime power is the maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load when operated for an unlimited number of hours per year under the agreed operating conditions with the maintenance intervals and procedures being carried out as prescribed by the manufacturer. The permissible average power output over 24 hours of operation shall not exceed 70 % of the PRP.

**Emergency Standby Power (ESP):**

According to ISO 8528-1:2018, Emergency standby power is the maximum power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 hours of operation per year with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. The permissible average power output over 24 hours of operation shall not exceed 70 % of the ESP

ENGINE		PRIME	STANDBY
Rated Output	kW	120	132
Manufacturer		Cummins	
Model		6BTA5.9-G2	
Number of Cylinders and arrangement		4 Cycle; In-line; 6 Cylinder Diesel	
Aspiration Type		Turbocharged,Air-air after-cooled	
Bore and Stroke	mm	102X120	
Compression Ratio		17.0:1	
Cooling System		Water-cooled	
Engine Speed/Frequency	rpm/Hz	1800/60HZ	
Coolant Capacity	L	30	
Starting System		Electric 24 volt DC	
Displacement	L	5.9	
Lubricant system Capacity	L	16.3	

Battery Volatge / Capacity		24VDC			
Governor	Type	Electronic			
Air Filter	Type	Dry			
Fuel Consumption	Load	100%	75%	50%	25%
	L/h	29.7	22.0	15.4	8.8

**ENGINE:**Industrial 4 stroke cooled diesel engine complete with air,fuel and oil filters,electric starting and charging equipment,engine protection against low water level.

**COOLING:**Radiator and colling fan complete with protection guards,designed to cool engine at specified output in air temperatures upto 50 °C,radiators suitable for higher temperatures are available.Low water level protection fitted as standard.

**ELECTRICAL SYSTEM:**12/24V upto.Axial type starter motor,battery charging alternator,high capacity lead acid battery,and battery tray mounted on the generator base frame,and heavy duty interconnecting cable with terminations.

**EXHAUST SYSTEM:**Heavy duty industrial exhaust silencer with flexible piping.

ALTERNATOR MANUFACTURER	STAMFORD	LEROY SOMER	PRIME POWER
Model	UCI274D	TAL-A44-E	SMG274D
Excitation System	Self-excited, brushless		
Number of Poles	4		
Connection Type	Star-Series		
Insulation Class	Class H		
Voltage Regulator	A.V.R. (Electronic)		
Bracker Type	Single bearing		
Steady Voltage Precision	± 1%		
Couping System	Flexible disc		
Coating Type	Standard ( Vacuum impregnation )		
Underspeed Protection	Standard		
Ingress Protection Rating	IP23		
Wave Form NEMA=TIF	<50		

**CONTROL PANEL: COMAP AMF20 Or DSE7320**

**Auto Mains Failure Control Panel**

Panel equipments:

- Δ Control with AMF module
- Δ Static battery charger
- Δ Emergency stop push button



**a) Generating set control module features:**

- Δ The module is used to monitor main supply and starts and stops of a standby generating set
- Δ Micro-processor based design
- Δ Automatic control of main and generator contactors
- Δ Monitors engine performance and AC power output LED alarm indication

**c) Alarms:**

- Δ Over and Under Speed
- Δ Low and High Battery Volt.
- Δ Start and Stop Failure
- Δ Charge fail

- Δ Front panel configuration of timers and alarm trip points
- Δ CAN and magnetic pick-up versions(specify on ordering)
- Δ Easy push button control
- Δ STOP/RESET - MANUAL - AUTO - TEST – START

- Δ Over Current
- Δ Under / Over Generator Voltage
- Δ Low Oil Pressure
- Δ Emergency stop
- Δ High engine temperature

**b) Metering via LED display:**

- Δ Generator Volts (L-L / L-N)      Generator kVA
- Δ Engine oil pressure (PSI-Bar)      Generator kW
- Δ Generator Ampere (L1,L2,L3)      Generator Cos (σ)
- Δ Engine temperature (°C&°F)
- Δ Generator Frequency (Hz)
- Δ Engine run hours
- Δ Mains Volts (Ph-Ph/Ph-N)

**d) LED indications**

- Δ Mains available
- Δ Generator available
- Δ Mains on load
- Δ Generator on load

**Voltage Regulation**

- Δ Voltage regulation maintained within ±0.5%      Δ From no load to full load
- Δ Between 0.8 and 1.0 lagging and unity      Δ At speed droop variation upto 4.5%

**Frequency Adjustable Ratio**

Change load from 0-100%,within 1.0%( electric speed regulator),within 4.5%( mechanical speed regulator)

**Frequency Undulation**

- Δ Load from 0-100%,frequency undulation within 0.25%      Δ Effect factor of Telecom
- Δ No load wire volts max undulation ration\ within 1.8%      Δ TIF better than 50
- Δ Three Pharse balanced load in the order of 5%      Δ THF to IEC60034 Part 40 better than 2%

**Robust Corrosion Resistant Construction**

- Δ Black finish stainless stell lock and hinges      Δ Two large doors on each side
- Δ Body made from steelcomponents treated with polyester powder coating
- Δ Lube oil and cooling water drains pipes to exterior of the enclosure

**Security and Safety**

- Δ Control panel viewing window in a lockable access door      Δ Cooling fan and battery charging alternator fully guarded
- Δ Emergency stop buttom mounted on enclosure interior      Δ Exhaust silencing system totally enclosed for operator safely



Generating Sets Optional Features				
Engine	Alternator	Generator Sets	Fuel System	Canopy
<ul style="list-style-type: none"> <li>Δ Water Jacket Preheater</li> <li>Δ Oil Preheater</li> <li>Δ Engine oil feeding and drain pump</li> </ul>	<ul style="list-style-type: none"> <li>Δ Winding Temperature Measuring Instrument</li> <li>Δ Alternator Preheater</li> <li>Δ PMG</li> <li>Δ Anti-damp and anti-corrosion treatment</li> <li>Δ Anti-condensation heater</li> </ul>	<ul style="list-style-type: none"> <li>Δ Auto Transfer Switch</li> <li>Δ Parallel control panels</li> <li>Δ Trailer type Gensets</li> <li>Δ Residential Silencer</li> <li>Δ Bulk fuel tank</li> </ul>	<ul style="list-style-type: none"> <li>Δ Low fuel level alarm shutdown</li> <li>Δ Automatic Fuel Filling System</li> </ul>	<ul style="list-style-type: none"> <li>Δ Super silent type</li> </ul>

**Quality Standards**

ISO9001:2000,ISO14000,ISO3046	BS5514,AS1359,ICE34
ISO8528 BS4999	CE Compliance

**Gensets Dimensions & Weight & Fuel Tank Capacity**

Open type:LxWxH (mm),Dry Weight / Kgs, Fuel tank ( L )	Silent type:LxWxH (mm), Dry Weight / Kgs,Fuel tank ( L )
2200*950*1530,1400 KGS,260L	3200*1080*2000, 1650kgs,280L

**Local Distributor:**



FUZHOU SUNSHINE MACHINERY CO.,LIMITED  
 Fuzhou, Fujian, China.

Tel:86-591-88204179 FAX:86-591-87723357  
 Email: sales@sunshinegenerator.com www.primepowergenset.com



PRIME POWER reserves the right to modify the characteristics of its product at any time in order to incorporate the latest technological developments. The information contained in this document may therefore be changed without notice.