

# MODEL: SMI880 INDUSTRIAL RANGE Powered by MITSUBISHI















#### DIESEL GENERATING SET 400/230 V - 50 Hz - 3PHASE

POWER RATING		PRIME	STANDBY	
POWER	kVA	800	880	
	kW	640	704	
Rated Speed	r.p.m	1500		
Available Voltages	V	400/230 - 380/220-415/240V-440/254 etc		
Rated at power factor	Cos Phi	0.8		

Standard Reference Conditions: 25°C (77°F) Air Inlet Temp, 100m(328 ft) A.S.L. 30% relative humidity.

#### Prime Power (PRP):

According to ISO 8528-1:2018, Prime power is the maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load when operated for an unlimited number of hours per year under the agreed operating conditions with the maintenance intervals and procedures being carried out as prescribed by the manufacturer. The permissible average power output over 24 hours of operation shall not exceed 70 % of the PRP.

#### **Emergency Standby Power (ESP):**

According to ISO 8528-1:2018, Emergency standby power is the maximum power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 hours of operation per year with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. The permissible average power output over 24 hours of operation shall not exceed 70 % of the ESP

ENGINE		PRIME	STANDBY	
Rated Output	kW	657	724	
Manufacturer		MITSUBISHI		
Model		S12A2-PTA		
Number of Cylindirs and arrangement		4 Cycle; 12V Cylinder Diesel		
Aspiration Type		Turbo-Charged, After Cooler		
Bore and Stroke	mm	150X160		
Compresion Ratio		14.5:1		
Cooling System		Water-cooled		
Engine Speed/Frequency	rpm/Hz	1500/50HZ		
Coolant Capacity Engine Only	L	215		
Starting System		Electric 24 volt DC		
Displacement	L	33.96		
Lubricant system Capacity	L	120		



# MODEL: SMI880 INDUSTRIAL RANGE Powered by MITSUBISHI

Battery Volatge / Capacity		24VDC			
Governor	Туре	Electrical			
Air Filter	Туре	Dry			
Fuel Consumption	Load	100%	75%	50%	25%
	L/h	175.0	135.0	90.0	48.0

**ENGINE**:Industrial 4 stroke cooled diesel engine complete with air,fuel and oil filters,electric starting and charging equipment,engine protection against low water level.

**COOLING:**Radiator and colling fan complete with protection guards,designed to cool engine at specified output in air temperatures upto 50 °C,radiators suitable for higher temperatures are available.Low water level protection fitted as standard.

**ELECTRICAL SYSTEM:**12/24V upto.Axial type starter motor,battery charging alternator,high capacity lead acid battery,and battery tray mounted on the generator base frame,and heavy duty interconnecting cable with terminations.

**EXHAUST SYSTEM:** Heavy duty industrial exhauset silencer with flexible piping.

ALTERNATOR MANUFACTURER	STAMFORD	LEROY SOMER	PRIME POWER	
Model	LVI634G	TAL-A49-B	SMG634G	
Excitation System	Self-excited, brushless			
Number of Poles	4			
Connection Type	Star-Series			
Insulation Class	Class H			
Voltage Regulator	A.V.R. (Electronic)			
Bracker Type	Single bearing			
Steady Voltage Precision	± 1%			
Couping System	Flexible disc			
Coating Type	Standard ( Vacuum impregnation )			
Underspeed Protection	Standard			
Ingress Protection Rating	IP23			
Wave Form NEMA=TIF	<50			

#### CONTROL PANEL: COMAP AMF20 Or DSE7320

#### **Auto Mains Failure Control Panel**

Panel equipments:

Δ Control with AMF module

Δ Static battery charger

Δ Emergency stop push button





#### a) Generating set control module features:

 $\Delta$  The module is used to monitor main supply and starts and stops of a standby generating set

 $\Delta$  Micro-processor based design

 $\Delta$  Automatic control of main and generator contactors

 $\Delta$  Monitors engine performance and AC power output LED alarm indication

#### c) Alarms:

Δ Over and Under Speed

Δ Low and High Battery Volt.

 $\Delta$  Start and Stop Failure

 $\Delta$  Charge fail



# MODEL: SMI880 INDUSTRIAL RANGE Powered by MITSUBISHI

 $\Delta$  Front panel configuration of timers and alarm trip points

Δ CAN and magnetic pick-up versions(specify on ordering)

Δ Easy push button control

Δ STOP/RESET - MANUAL - AUTO - TEST - START

#### b) Metering via LED display:

 $\begin{array}{ll} \Delta \ \mbox{Generator Volts (L-L / L-N)} & \mbox{Generator kVA} \\ \Delta \ \mbox{Engine oil pressure (PSI-Bar)} & \mbox{Generator kW} \\ \Delta \ \mbox{Generator Ampere (L1,L2,L3)} & \mbox{Generator Cos } (\sigma) \end{array}$ 

 $\Delta$  Engine temperature (°C&°F)  $\Delta$  Generator Frequency (Hz)

Δ Engine run hours

Δ Mains Volts (Ph-Ph/Ph-N)

Δ Over Current

Δ Under / Over Generator Voltage

Δ Low Oil Pressure

Δ Emergency stop

Δ High engine temperature

#### d) LED indications

Δ Mains available

Δ Generator available

Δ Mains on load

Δ Generator on load

#### Voltage Regulation

 $\Delta$  Voltage regulation maintanined within  $\pm 0.5\%$   $\Delta$  From no load to full load

 $\Delta$  Between 0.8 and 1.0 lagging and unity  $\Delta$  At speed droop variation upto 4.5%

#### Frequency Adjustable Ratio

Change load from 0-100%, within 1.0% (electric speed regulator), within 4.5% (mechanical speed regulator)

#### Frequency Undulation

 $\Delta$  Load from 0-100%, frequency undulation within 0.25%  $\Delta$  Effect factor of Telecom  $\Delta$  No load wire volts max undulation ration\ within 1.8%  $\Delta$  TIF better than 50

 $\Delta$  Three Phrase balanced load in the order of 5%  $\Delta$  THF to IEC60034 Part 40 better than 2%

#### Robust Corrosion Resustant Construction

 $\Delta$  Black finish stainless stell lock and hinges  $\Delta$  Two large doors on each side

 $\Delta$  Body made from steel components treated with polyester powder coating

 $\Delta$  Lube oil and cooling water drains pipes to exterior of the enclosure

#### Security and Safety

Δ Control panel viewing window in a lockable access door Δ Cooling fan and battery charging alternator fully guarded

Δ Emergency stop buttom mounted on enclosure interior Δ Exhaust silencing system totally enclosed for operator safely





### MODEL: SMI880

### INDUSTRIAL RANGE Powered by MITSUBISHI

Generating Sets Optional Features					
Engine	Alternator	Generator Sets	Fuel System	Canopy	
Δ Water Jacket Preheater	Δ Winding Temperatrue Measuring Instrumeent	Δ Auto Transfter Switch	Δ Low fuel level alarm shutdown	Δ Super silent type	
Δ Oil Preheater	Δ Alternator Preheater	Δ Parallel control panels	Δ Automatic Fuel Filling		
ΔEngine oil feeding and drain pump	Δ PMG	Δ Trailer type Gensets	System		
	Δ Anti-damp and anti- corrosion treatment	Δ Residential Silencer			
	Δ Anti-condensation heater	Δ Bulk fuel tank			
	·				

#### **Quality Standards**

ISO9001:2000,ISO14000,ISO3046

BS5514,AS1359,ICE34

ISO8528 BS4999

**CE** Compliance

#### Gensets Dimensions & Weight & Fuel Tank Capacity

Open type:LxWxH (mm),Dry Weight / Kgs, Fuel tank (  $\mbox{L}$  )

Silent type:LxWxH (mm), Dry Weight / Kgs,Fuel tank (  $\mbox{L}$  )

4100\*1725\*2080, 7500kgs

6058\*2438\*2591,11429 kgs

Local Distributor:






FUZHOU SUNSHINE MACHINERY CO.,LIMITED Fuzhou, Fujian, China.

PRIME PEWER

Tel:86-591-88204179 FAX:86-591-87723357

Email: sales@sunshinegenerator.com www.primepowergenset.com

PRIME POWER reserves the right to modify the characteristics of its product at any time in order to incorporate the latest technological developments. The information contained in this document may therefore be changed without notice.